INTERNATIONAL POINT OF SALE

Installation instructions for Gprinter GP Series



This guide will go over how to install the GPrinter GP-80250IIIN and GP-80250IIN drivers and set them up with CornerStore.

Please make sure you are using a straight through Serial Cable.

Driver Instructions

Step 1: Download and Run the Executable from http://cornerstorepos.com/downloads/hardware/GPOPOSSetup.zip



Step 2: Press Next >

😽 Setup - GP OPOS ADK Version 1.0E				
	Welcome to the GP OPOS ADK Version 1.0E Setup Wizard			
	This will install GP OPOS ADK Version 1.0E on your computer.			
	It is recommended that you close all other applications before continuing.			
	Click Next to continue, or Cancel to exit Setup.			
	Next > Cancel			

Step 3: Press Next >



Step 4: Press Next >

😽 Setup - GP OPOS ADK Version 1.0E
Select Start Menu Folder Where should Setup place the program's shortcuts?
Setup will create the program's shortcuts in the following Start Menu folder.
To continue, click Next. If you would like to select a different folder, click Browse.
GP OPOS Browse
< Back Next > Cancel

Step 5: Click install.



Step 6: Press Finish.



Step 7: Select PosPrinter and GP-80220II. Then select "Add LDN"

🐥 GF	GP OPOS ADK Version 1.0E					×
Dev	DeviceCalss DeviceModel					
	PosPrinter 💌		GP-8022011	•		
Dev	vicel ist					
100	NOCEISC	1		1	Add LDN	
	LDN	DeviceModel	UsingPort	DeviceDescrip		
					Configure	
					Remove	
					CheckHealth	
						1
					Cancel	1

Step 8: Select the proper **COM Port**. Then put in the proper information into the window.

Note: To find this information, turn off the printer, press and hold the feed button, then turn the printer on and not letting go of the feed button till the paper light turns off. Press **OK** when you are done.

ConfigureDialog	
LDN Printor	Serial Port Setting
	BaudRate: 19200
GP-8022011	DataBits: 8
Port	StopBits: 1
COM1 🗨	HandShake: DTR/DSR -
OK Cancel	Parity: NONE

Step 9: You should see your printer now.

Add LDN Configure Remove CheckHealth

Step 10: Select the name you set up, then press CheckHealth

Chech Health Dialog 🛛 🔀				
Push To Start CheckHealth				
Result:				
Exit CheckHealth				

Step 11: Press "Push To Start CheckHealth", you should get OPOS_SUCESS

Chech Health Dialog 🛛 🔀				
Push To, Start, CheckHealth				
Result:				
OPOS_SUCCESS				
Exit CheckHealth				

Step 12: For Device Class, select Cash Drawer, and Device model should be Standard. Press Add LDN

DeviceCalss DeviceModel	
CashDrawer Standard	
DeviceList	Add LDN
	Configure
	Remove
	CheckHealth
	Cancel
7 1-866-468-5767 or 201-928-0222	International Point of Sale

Step 13: Add a name for the drawer, select the same information as the printer.

ConfigureDialog	
LDN drawer	Serial Port Setting
DeviceModel	BaudRate: 19200 ▼ DataBits: 8 ▼
Port	StopBits: 1
COM3	HandShake: DTR/DSR - Parity: NONE -
	,

Step 14: Press the name you selected in the field, then press CheckHealth

ADK Version 1.0E				
DeviceCalss DeviceModel				
Drawer 🔹 Standard 💌				
Add LDN				
DeviceModel UsingPort DeviceDescrip				
r Standard COM3 GP POSPrinter Configure				
Remove				
CheckHealth				
Cancel				

8 1-866-468-5767 or 201-928-0222

Step 15: Press **"Push To Start CheckHealth"**, the drawer should open and the **OPOS_SUCCESS** will appear on screen.

Check Health Dialog 🛛 🛛 🔀				
Push To Start CheckHealth				
Result:				
OPOS_SUCCESS				
Exit CheckHealth				

Setting up the printer with CornerStore

Go to Setup > Hardware Setup, select the G-Printer and when you want your receipt printer to print.

SetupHardware					
Hardware Setup					
Select Type Installed Printers Do you want to print receipt?					
⊙ Rece ○ Labe	Type Installed Printers HP LaserJet 400 MFP M HP LaserJet 400 MFP M GP-80250 Series Generic / Text Only Auto Send To OneNote \\BRN_D96569\BINARY BTP-R880NP CT-S310II_1 GP-80220II PP Demo Thermall		 Yes No CC Only Prompt Receipt option Short Description Full Description 		
					Save Exit

Select the cash drawers tab, and select the Standard cash drawer, Click Save then exit.

SetupHardware SetupHardwar
Hardware Setup
Printers Cash Drawers Pole Display Pin Pad Other
Installed Cash Drawers
BTP-R880NPDrawer1 CR Demo CT-S310II_1.CD1
Standard
Save Exit

Your printer is now ready to use with CornerStore!